

Sigen Hybrid Inverter

50.0 / 60.0 / 80.0 / 100.0 / 110.0 kW



- Seamless switchover, ensuring 0ms load-side disruption operation
- 150% overload for 10s, handling impact loads for smooth device startup
- Minimal size & weight in the same power range, ensures simple installation
- Multi-unit connection via Energy Gateway, flexible expansion from kW to MW
- DC coupling micro-grid solution, simplifies configuration & boosts efficiency

Sigen PV	50M1-HYB	60M1-HYB	80M1-HYB	100M1-HYB	110M1-HYB	Units	
DC Input (PV)							
Max. PV input power	100,000	120,000	160,000	200,000	220,000	Wp	
Max. DC input voltage						1,100	V
Nominal DC input voltage						600 @380/400 Vac, 720 @480 Vac	V
Start-up voltage						180	V
MPPT voltage range						160 - 1,000	V
Number of MPP trackers	4	5	6	8	8		
Number of PV strings per MPPT						2	
Max. input current per MPPT						40	A
Max. short-circuit current per MPPT						60	A
DC Input (Battery)							
Battery module models						SigenStack BAT 12.0	
Battery controller models						SigenStack BC M2-0.5C-BST / SigenStack BC M2-1C-BST	
System configuration quantity range ¹						4 - 21	pcs
Max. charge power	55,000	66,000	88,000	110,000	121,000	W	
Max. discharge power	55,000	66,000	88,000	110,000	121,000	W	
Max. operating current						180	A
AC Output (On-grid)							
Nominal output active power	50,000	60,000	80,000	100,000	110,000	W	
Max. output apparent power	55,000	66,000	88,000	110,000	121,000	VA	
Max. output active power (cosφ=1)	55,000	66,000	88,000	110,000	121,000	W	
Nominal output current @380Vac	76.0	91.2	121.5	151.9	167.1	A	
Nominal output current @400Vac	72.5	87.0	115.9	144.9	159.4	A	
Nominal output current @480Vac	60.2	72.2	96.3	120.3	132.4	A	
Max. output current @380/400Vac	83.6	100.3	133.7	167.1	183.8	A	
Max. output current @480Vac	66.2	79.4	105.9	132.4	145.6	A	
Nominal output voltage						380 / 400 / 480, 3W+N+PE	Vac
Nominal grid frequency						50 / 60	Hz
Power factor						0.8 leading - 0.8 lagging	
Total current harmonic distortion						THDi < 3%	
AC Input (On-grid)							
Max. input apparent power	100,000	120,000	160,000	160,000	160,000	VA	
Max. input current @380/400Vac	151.9	182.3	243.1	243.1	243.1	A	
Max. input current @480Vac	120.3	144.4	192.5	192.5	192.5	A	
Max. continuous AC passthrough (grid to load)	83.6	100.3	133.7	167.1	183.8	A	
AC Output (Backup)							
Nominal output active power	50,000	60,000	80,000	100,000	110,000	W	
Max. output apparent power	55,000	66,000	88,000	110,000	121,000	VA	
Peak output power (10 seconds)	75,000	90,000	120,000	150,000	150,000	W	
Nominal output voltage						380 / 400 / 480, 3W+N+PE	V
Nominal output frequency						50 / 60	Hz
Power factor						0.8 leading - 0.8 lagging	
Total voltage harmonic distortion						THDv < 3%	
Disruption time of backup switch ²						0	ms
Efficiency							
Max. efficiency @380/400 Vac						98.3%	
European efficiency @380/400 Vac	97.9%	97.9%	98.0%	98.0%	98.0%		
Max. efficiency @480 Vac						98.5%	
European efficiency @480 Vac	98.2%	98.2%	98.3%	98.3%	98.3%		
Protection							
Safety protection feature	DC reverse polarity protection, Insulation monitoring, Residual current monitoring, Arc fault circuit interrupter, AC overcurrent/overvoltage/short-circuit protection. Type II DC/AC surge protection, Anti-islanding protection						
General Data							
Dimensions (W / H / D)						1097 / 668 / 340	mm
Weight	99	102	102	105	105	kg	
Storage temperature range						-40 - 70	°C
Operating temperature range						-30 - 60	°C
Relative humidity range						0% - 100%	
Max. operating altitude						5,000 (Derating at 4,000m)	m
Cooling						Smart air cooling	
Ingress protection rating						IP66	
Communication						WLAN / Fast Ethernet / RS485 / Sigen CommMod (4G/3G/2G)	
Standard Compliance							
Standard ³	IEC / EN 62109-1, IEC / EN 62109-2, IEC / EN 61000-6-1, IEC / EN 61000-6-2						

- The requirements for the PV string open-circuit voltage in a PV+ESS DC coupling system are as follows: 1) When the system is configured with ≥19 battery modules, the string open-circuit voltage should meet the following minimum requirements: 1.1) If configured with 21 battery modules, the string open-circuit voltage should be > 935 V; 1.2) If configured with 20 battery modules, the string open-circuit voltage should be > 870 V; 1.3) If configured with 19 battery modules, the string open-circuit voltage should be > 805 V. 2) When the system is configured with 4 to 18 battery modules, the string open-circuit voltage has no special requirements.
- This refers to the load-side disruption time. Test conditions: In the open-circuit state of the power grid, the total power of the Sigen Hybrid Inverter is higher than the total power of the loads.
- For all standards refer to the certificates category on the Sigenenergy website.
- For Sigen energy gateway connections, the inverter should be connected to the gateway via its AC output port (Grid).
- The information in this document reflects the current state of technology and is subject to change without notice. For the latest updates, please refer to the Sigenenergy website.

Disclaimer: The information in this file is provided on an "as is" basis. To the fullest extent permitted by law, Sigenenergy Technology Co., Ltd. excludes all representations and warranties relating to this file and its contents or which is or may be provided by any affiliates or any other third party, including in relation to any inaccuracies or omissions in this file.

